## B.E. (Mechanical) (Sem-VIII) (CBSGS)

Paper / Subject Code: 53305 / 2)Renewable Energy Sources

Q. P. Code: 50645

Date-13/12/1

NI D 1	Time: 3 hours Mai	rks : 80
N. B. I	) Question No. 1 is compulsory	
2	2) Attempt any three questions out of remaining five questions	
3	B) Figures to right indicate full marks	
4	4) Assume suitable data if necessary	
Q. 1.	Write short note on any four	
(	a) Define Solar Constant Air Mass Call Alive to the	20
	a) Define Solar Constant, Air Mass, Solar Altitude Angle, Angle of Incidence	<b>3</b>
	b) Wind Energy Site Selection	왕정 때문
	c) Energy Audit	
	d) Energy Plantation	
	e) Classification of Energy Sources	
Q. 2. a)	Calculate Solar altitude angle, incident angle and collector efficiency if:	3333
	Location, Pune: (18 <sup>0</sup> 32'N, 73 <sup>0</sup> 51'E)	10
	Day and Time: May 15, 11A.M.	
	Annual avarage intensity of all the state of	
	Annual average intensity of solar radiation 400 W/m <sup>2</sup>	
	Collector tilt: Latitude angle	
	No. of glass covers: 2	
	Heat removal factor: 0.85	
	Transmittance of glass: 0.88	
	Absorptance of glass: 0.90	
	Top loss coefficient: 7 W/m <sup>2</sup> °C	
	Collector fluid temperature: 73 <sup>o</sup> C	
	Ambient temperature: 28°C	
	Diffusive reflectance for two covers: 0.24	
	Diffusive reflectance for two covers: 0.24	
Q. 2 b)	Explain the construction details and working of KVIC biogas digester	10
Q. 3. a)	Explain the techniques suggested for maintaining the Biogas production.	10
Š	2013년 18일 2013년 18일 2013년 10일 2013년 2013	10
Q. 3. b)		: 10
	(19 <sup>0</sup> 07'N, 72 <sup>0</sup> 51'E) during the month of March, if the average sunshine how	oai 10
	per day is 9.5. Assume the value of $a = 0.31$ and $b = 0.43$	irs
	$r^{2} = 0.51$ and $r^{2} = 0.43$	
Q. 4. a)	State various parameters which affects performance of solar collectors	
	various parameters which affects performance of solar collectors	04
(2. 4. b)	What is wave energy? Explain any one wave energy conversion system	06
(). 4. c)	· (선택) (선택) 사고 전 선택 (선택) (선택) (선택) (선택) (선택) (선택) (선택) (	
¿. 4. c)	Calculate the number of animals and volume of biodigester required to produce the production of the pr	ce 10
	power for nousehold which has power requirement of 0.8 KW for lighting ar	ıd
	cooking purpose.	
	Take C.V. of methane 28 MJ/ m <sup>3</sup>	
	Burner efficiency: 65%	
	Retention period: 25 days	
	Dry matter per animal per day is 1.8 kg	
	Density of dry matter in slurry in digester is 50 kg/m <sup>3</sup>	
	Biogas yield is 0.3 m <sup>3</sup> per kg of dry input	•
	Methane proportion in biogas is 0.7	
	AND THE DESCRIPTION IN DIOMAS 18 () /	

## Paper / Subject Code: 53305 / 2)Renewable Energy Sources

Q. P. Code: 50645

Q. 5. a)	State and explain design considerations in Wind turbine design	08
Q. 5. b)	Describe 'Closed Cycle' OTEC system with its advantages over 'Open Cycle' system.	00
Q. 5. c)	State the advantages and disadvantages of geothermal energy	06
Q. 6.	Write short note on any Four a) Small head hydro power development b) Application of Wind Energy c) Producer Gas d) Total Energy Conversion e) Fuel Cell	20

\*\*\*\*\*\*\*\*\*\*\*